

Date of Change	Order Changed	Changes Noted in Yellow on order
06/30/2006		Please review the specific order for changes
06/30/2006	U25 (Post Migration, Analog to Digital Loop Regrade)	Added new order
06/30/2006	U26 (Post Migration, Digital to Analog Loop Regrade)	Added new order

Activity	Description		Service Type
Migration "as specified"	Migrate to Local Number Portability		Business POTS
	With Batch Hot Cut		
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<9722732425>
17	D/TSENT	Date and Time Sent	<200606090800>
19	DDD	Desired Date Due	<20060609>
24	DFDT	Desired Frame DueTime	2345 (See Footnote 1)
29	CHC	Coordinated Hot Cut	 (See Footnote 2)
30	REQTYP	Request Type	BB (See Footnote 3)
32	SLI	Sub Loop Indicator	S (See Footnote 4)
33	ACT	Activity	V
37	EXP	Expedite	(See Footnote 5)
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider Identification	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<IRNGTXXBDS1>
61	LSO	Local Serving Office	<972273>
62	TOS	Type of Service	11F1 (See Footnote 6)
64	NC	Network Channel Code	LX--
66	NCI	Network Channel Interface Code	02QC2.00F
77	NPDI	Number Portability Direction Indicator	D
105	INIT	Initiator Name	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>
115	IMPCON	Implementation Contact	<Mary Williams> (See Footnote 7)
116	TEL NO	Telephone Number	<8134383000> (See Footnote 7)

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address House Number	<210>
15	SASD	Service	<S>
16	SASN	Service Address Street Name	<MAIN>
17	SATH	Service Address Thoroughfare	<ST>
26	CITY	City	<Anytown>
27	STATE	State/Province	<TX>
28	ZIP	Zip/Postal Code	<75060>
45	EATN	Existing Account Telephone Number	<9722732425>
Loop Service with Number Portability Form (LSNP)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
Service Details (SD)			
8	LOCNUM	Location Number	<001>
9	LNUM	Line Number	<00001>
11	LNA	Line Activity	V
19	TDT	Ten Digit Trigger	Y
29	SHELF	Shelf	<ABC017>
30	SLOT	Slot	<1001>
43	PORTED NBR	Ported Telephone Number	<9722732425>
46	NPT	Number Portability Type	D

Directory Listing Form 1 (DL)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
9	LACT	Listing Activity Indicator	0
10	ALI	Alpha/Numeric Listing Identifier Code	<100>
11	RTY	Record Type	<LML>
12	LTY	Listing Type	<3>
14	STYC	Style Code	<SL>
15	TOA	Type of Account	
16	DOI	Degree of Indent	<0>
18	LOCNUM	Location Number	<001>
19	DLNUM	Directory Listing Number	<0001>
20	MTN	Main Telephone Number	<9722732425>
38	LTN	Listing Telephone Number	<9722732425>
43	LEX	Local Exchange	<972273>
46	LNLN	Listed Name Last	<Best>
47	LNFN	Listed Name First	<Food Shop>
68	LANO	Listed Address House Number	<210>
70	LASD	Listed Address Street Directional Prefix	<S>
71	LASN	Listed Address Street Name	<Main>
72	LATH	Listed Address Thoroughfare	<St>
75	LALOC	Listed Address Locality	<Anytown>
77	LAZC	Listed Address Zip/Postal Code	<75060>

Directory Listing Form (DL) 2			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
5	ATN	Account Telephone Number	<9722732425>
9	LACT	Listing Activity Indicator	I
10	ALI	Alpha/Numeric Listing Identifier Code	<100>
11	RTY	Record Type	<LML>
12	LTY	Listing Type	<1>
14	STYC	Style Code	<SL>
15	TOA	Type of Account	
16	DOI	Degree of Indent	<0>
18	LOCNUM	Location Number	<001>
19	DLNUM	Directory Listing Number	<0001>
20	MTN	Main Telephone Number	<9722732425>
38	LTN	Listing Telephone Number	<9722732425>
43	LEX	Local Exchange	<972273>
46	LNLN	Listed Name Last	<Best>
47	LNFN	Listed Name First	<Food Shop>
68	LANO	Listed Address House Number	<210>
70	LASD	Listed Address Street Directional Prefix	<S>
71	LASN	Listed Address Street Name	<Main>
72	LATH	Listed Address Thoroughfare	<St>
75	LALOC	Listed Address Locality	<Anytown>
77	LAZC	Listed Address Zip/Postal Code	<75060>

Footnotes			
			1. Time in the DFDT field should always be in Military Time (i.e. 0800 is 8:00 AM, 1300 is 1:00 PM, 1400 is 2:00 PM etc.). Time slots are allotted in 15-minute increments (i.e. 1315, 1330, 1345, 1400) and are scheduled on a first come first serve basis.
			1a. If CHC=A, DFDT must =2300.
			1b. If CHC=B, DFDT must =2345.
			2. This field may require manual intervention and coordination between the provider/customer
			2a. An entry in this field requires a single time entry in the DFDT field
			2b. If LSR has less than 20 LNUMs, CHC cannot =A.
			2c. A= Large Job Batch Hot Cut B= Y= Yes
			3. If CHC=A,B then REQ TYP must =AB,BB.
			4. If CHC=A,B then SLI must =S.
			5. Prohibited if CHC=A,B
			6. Refer to Business Rules for TOS guidelines and requirements
			7. Required if DFDT is populated.

Activity	Description	Service Type	
Post Migration	Change of Analog Loop	Business POTS	
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZZ>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<817TX00019>
17	D/TSENT	Date and Time Sent	<200606090800>
19	DDD	Desired Date Due	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	C
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider Identification	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<SPTWTXXADS0>
61	LSO	Local Serving Office	<817523>
62	TOS	Type of Service	12F1
64	NC	Network Channel Code	LX-N
66	NCI	Network Channel Interface Code	02QC2.OOF
105	INIT	Initiator Name	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address Number	<113>
16	SASN	Service Address Street Name	<SECOND>
17	SATH	Service Address Street Type	<ST>
26	CITY	City	<Anytown>
27	STATE	State/Province	<TX>
28	ZIP	Zip/Postal Code	<76082>
45	EATN	Existing Account Telephone Number	<817TX00019>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	C
17	ECCKT	Exchange Company Circuit ID	<2V.TXNU.000030. .GTEC>
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1001>

Activity	Description		Service Type
New Service	Add Analog Loop		Business POTS
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	N
17	D/TSENT	Date and Time Sent	<200606090800>
19	DDD	Desired Date Due	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	N
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider Identification	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<CRWDFLXA96H>
61	LSO	Local Serving Office	<813960>
62	TOS	Type of Service	11F1 (See Footnote 1)
64	NC	Network Channel Code	LX--
66	NCI	Network Channel Interface Code	02QC2.OOF
105	INIT	Initiator Name	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>
115	IMPCON	Implementation Contact	<Mary Williams> (See Footnote 2)
116	TEL NO	Telephone Number	<8134383000> (See Footnote 2)

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	N
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address Number	<14917>
16	SASN	Service Address Street Name	<ZAMBITO>
17	SATH	Service Address Street Type	<RD>
26	CITY	City	<Anytown>
27	STATE	State/Province	<FL>
28	ZIP	Zip/Postal Code	<33618>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	N
Service Detail (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	N
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1001>
Service Detail (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00002>
9	LNA	Line Activity	N
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1002>
Service Detail (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00003>
9	LNA	Line Activity	N
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1003>
Service Detail (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00004>
9	LNA	Line Activity	N
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1004>

Service Detail (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00005>
9	LNA	Line Activity	N
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1005>
Directory Listing Form (DL)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZZ>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
9	LACT	Listing Activity Indicator	N
10	ALI	Alpha/Numeric Listing Identifier Code	<100>
11	RTY	Record Type	<LML>
12	LTY	Listing Type	<1>
14	STYC	Style Code	<SL>
15	TOA	Type of Account	
16	DOI	Degree of Indent	<0>
18	LOCNUM	Location Number	<001>
19	DLNUM	Directory Listing Reference Number	<0001>
20	MTN	Main Telephone Number	<N>
38	LTN	Listing Telephone Number	<N>
43	LEX	Local Exchange	<813960>
46	LNLN	Listed Name Last	<Best>
47	LNFN	Listed Name First	<Food Shop>
68	LANO	Listed Address Number	<14917>
71	LASN	Listed Address Street Name	<Zambito>
72	LATH	Listed Address Street Type	<Rd>
75	LALOC	Listed Address Locality	<Anytown>
75	LAZC	Listed Address Zip/Postal Code	<33618>
116	YPHV	Yellow Page Heading Verbiage	<NONE>
Footnote:			
			1. Use appropriate codes for Business or Residence service.
			2. Required when LNA=N or T. Implementation Contact TEL NO required when IMPCON field is populated.

Activity	Description	Service Type	
Migration "as specified"	Migrate 1 line to loop	Residence POTS	
	Change the TN to a new CLEC TN		
	Change directory listing		
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your Pon>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<(Clec TN)>
17	D/TSENT	Date Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	V
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider	<Z001>
40	RVER	Release Version	<9>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<KYSTFLXA92H>
61	LSO	Local Serving Office	<813920>
62	TOS	Type Of Service	21F1
64	NC	Network Channel Code	LX--
66	NCI	Network Channel Interface Code	02QC2.OOF
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>

End User Form (EU)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<(Clec TN)>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Jones, Tom>
13	SANO	Service Address Number	<14917>
16	SASN	Service Address Street Name	<ZAMBITO>
17	SATH	Service Address Street Type	<RD>
19	LD1	Location Designator 1	<APT>
20	LV1	Location Value 1	<100>
26	CITY	City	<Anytown>
27	STATE	State/Province	<FL>
28	ZIP	Zip/Postal Code	<33618>
45	EATN	Existing Account Telephone Number	<8139200001>
Disconnect Info 1			
65a	LOCNUM	Location Number	<001>
66	DNUM	Disconnect Line Number	<00001>
67	DISC NBR	Disconnect Telephone Number	<8139200001>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<(Clec TN)>
Service Detail (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	V
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<00194>

Directory Listing Form (DL)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your Pon>
3	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<(Clec TN)>
9	LACT	Listing Activity Indicator	N
10	ALI	Alpha/Numeric Listing Identifier Code	<100>
11	RTY	Record Type	LML
12	LTY	Listing Type	1
14	STYC	Style Code	SL
15	TOA	Type of Account	R
16	DOI	Degree of Indent	0
18	LOCNUM	Location Number	001
19	DLNUM	Directory Listing Reference Number	0001
20	MTN	Main Telephone Number	<(Clec TN)>
38	LTN	Listing Telephone Number	<(Clec TN)>
43	LEX	Local Exchange	<813920>
46	LNLN	Listed Name Last	<Jones>
47	LNFN	Listed Name First	<Tom>
68	LANO	Listed Address Number	<14917>
71	LASN	Listed Address Street Name	<Zambito>
72	LATH	Listed Address Street Type	<Rd>
75	LALOC	Listed Address Locality	<Anytown>
77	LAZC	Listed Address ZIP/Postal Code	<33618>

Activity	Description		Service Type
Disconnect	Disconnect UNE Analog Loop		Business POTS
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your Pon>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<727UB00086>
14	D/TSENT	Date Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	<S>
33	ACT	Activity	D
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider	<Z001>
40	RVER	Release Version	<9>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<SPBGFLXA89H>
61	LSO	Local Serving Office	<727825>
62	TOS	Type Of Service	1HF1
64	NC	Network Channel Code	LX-N
66	NCI	Network Channel Interface Code	02QC2.OOF
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>
End User Form (EU)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<727UB00086>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address Number	<821>
16	SASN	Service Address Street Name	<1ST AVE N>
19	LD1	Location Designator 1	<STE>
20	LV1	Location Value 1	<200>
26	CITY	City	<ST PETERSBURG>
27	STATE	State/Province	<FL>
28	ZIP	ZIP/Postal Code	<33701>

Activity	Description	Service Type	
New Service	New install of an xDSL Loop	Business xDSL	
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your Pon>
3	VER	Version	<01>
8	ATN	Account Telephone Number	N
17	D/TSENT	Date Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	N
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<CRWDFLXA96H>
61	LSO	Local Serving Office	<813960>
62	TOS	Type Of Service	12F1 (See Footnote 1)
64	NC	Network Channel Code	LX-N
66	NCI	Network Channel Interface Code	02QB5.00E
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>
115	IMPCON	Implementation Contact	<Mary Williams> (See Footnote 2)
116	TEL NO	Telephone Number	<8134383000> (See Footnote 2)
132	REMARKS	Remarks	<1500 kft>

End User Form (EU)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	N
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Jones, Tom>
13	SANO	Service Address Number	<14917>
16	SASN	Service Address Street Name	<ZAMBITO>
17	SATH	Service Address Street Type	<RD>
19	LD1	Location Designator 1	<STE>
20	LV1	Location Value 1	<209>
26	CITY	City	<TAMPA>
27	STATE	State/Province	<FL>
28	ZIP	ZIP/Postal Code	<33624>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	N
Service Detail (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1001>
Footnote:			
			1. Use appropriate codes for Business or Residence service.
			2. Required if ACT=N,C,M,T,V and any LNA or TACT=N,M,T.

Activity	Description	Service Type	
Post Migration	Change services	Business POTS	
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your Pon>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<817TX00019>
17	D/TSENT	Date Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	C
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<SPTWTXXADS0>
61	LSO	Local Serving Office	<817523>
62	TOS	Type Of Service	1HF1
64	NC	Network Channel Code	LX-N
66	NCI	Network Channel Interface Code	02QC2.OOF
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>

End User Form (EU)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address Number	<113>
15	SASD	Service Address Street Directional Prefix	<W>
16	SASN	Service Address Street Name	<SECOND>
17	SATH	Service Address Street Type	<ST>
19	LD1	Location Designator 1	<STE>
20	LV1	Location Value 1	<200>
26	CITY	City	<SPRINGTOWN>
27	STATE	State/Province	<TX>
28	ZIP	ZIP/Postal Code	<76082>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<817TX00019>
Service Detail (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	C
17	ECCKT	Exchange Company Circuit ID	2V.TXNU.000030.###.GTEC.
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1001>

Activity	Description	Service Type	
Post Migration	Add Line Splitting to an existing Platform POTS line	Residence POTS	
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your Pon>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<7273272659>
17	D/TSENT	Date Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	V
40	RVER	Release Version	<9>
43	CC	Company Code	<Z002>
45	NNSP	New Network Service Provider	<Z002>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<SKWYFLXADS0>
61	LSO	Local Serving Office	<727327>
62	TOS	Type Of Service	2PM1
64	NC	Network Channel Code	UR--
66	NCI	Network Channel Interface Code	04QSM.L05
71	LSP AUTH	Local Service Provider Authorization	<ZZ1>
72	LSP AUTH DATE	Local Service Provider Authorization Date	<20050215>
73	LSP AUTH NAME	Local Service Provider Authorization Name	<Jane Thomas>
87	ACNA	Access Customer Name Abbreviation	<ZZ1>
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>

End User Form (EU)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<7273272659>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Jones, Tom>
13	SANO	Service Address Number	<675>
16	SASN	Service Address Street Name	<S 37TH ST>
19	LD1	Location Designator 1	<APT>
20	LV1	Location Value 1	<103>
26	CITY	City	<ST PETERSBURG>
27	STATE	State/Province	<FL>
28	ZIP	ZIP/Postal Code	<33711>
45	EATN	Existing Account Telephone Number	<7273272659>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<7273272659>
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	V
10	SLTN	Shared Line Telephone Number	<7273272659>
34	SHELF	Shelf	<AB>
35	SLOT	Slot Port	<99>

Activity	Description	Service Type	
New Service	Intall Line Share Unbundled Sub-loop Arrangement	Residence Line Sharing	
	2-wire ADSL-R		
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your Pon>
3	VER	Version	<01>
8	ATN	Account Telephone Number	N
17	D/TSENT	Date Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	B
33	ACT	Activity	N
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<IRNGTXXBDS1>
61	LSO	Local Serving Office	<972253>
62	TOS	Type Of Service	2RF1 (See Footnote 1)
64	NC	Network Channel Code	UA--
66	NCI	Network Channel Interface Code	02QE9.005
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>
115	IMPCON	Implementation Contact	<Mary Williams> (See Footnote 2)
116	TEL NO	Telephone Number	<8134383000> (See Footnote 2)

End User Form (EU)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<N>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Jones, Tom>
13	SANO	Service Address Number	<210>
15	SASD	Service Address Street Directional Prefix	<S>
16	SASN	Service Address Street Name	<MAIN>
17	SATH	Service Address Street Type	<ST>
19	LD1	Location Designator 1	<STE>
20	LV1	Location Value 1	<201>
26	CITY	City	<IRVING>
27	STATE	State/Province	<TX>
28	ZIP	ZIP/Postal Code	<75060>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Telephone Number	<N>
Service Detail 1 (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	N
10	SLTN	Shared Line Telephone Number	<9722539374>
13	CKR	Customer Circuit Reference	<____ OR ____ - ____>
31	CBCID	Cross Box Cable Identification	<ABC123>
34	SHELF	Shelf	<NA>
35	SLOT	Slot Port	<99>
Service Detail 2 (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00002>
9	LNA	Line Activity	N
10	SLTN	Shared Line Telephone Number	<9722539374>
13	CKR	Customer Circuit Reference	<____ OR ____ - ____>
31	CBCID	Cross Box Cable Identification	<ABC123>
34	SHELF	Shelf	<NA>
35	SLOT	Slot Port	<99>

Footnote:			
			1. Use appropriate codes for Business or Residence service.
			2. Required if ACT=N,C,M,T,V and any LNA or TACT=N,M,T.

Activity	Description	Service Type	
Disconnect	Disconnect ADSL Service	Business ADSL	
No.	Field	Data Description	Wise/EDI Input
<i>Local Service Request Form (LSR)</i>			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your Pon>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<727SW07915>
17	D/TSENT	Date Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	D
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<PNLSFLXA53H>
61	LSO	Local Serving Office	<727530>
62	TOS	Type Of Service	1RF1
64	NC	Network Channel Code	UA--
66	NCI	Network Channel Interface Code	02QB9.005
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>
132	REMARKS	Remarks	<1500 kft>

End User Form (EU)			
1	PON	Purchase Order Number	<Your Pon>
2	VER	Version Indicator	<01>
4	ATN	Account Number	<727SW07915>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address Number	<5045>
16	SASN	Service Address Street Name	<EAST BAY>
17	SATH	Service Address Street Type	<DR>
19	LD1	Location Designator 1	<STE>
20	LV1	Location Value 1	<200>
26	CITY	City	<CLEARWATER>
27	STATE	State/Province	<FL>
28	ZIP	ZIP/Postal Code	<33764>
Disconnect Info			
65a	LOCNUM	Location Number	<001>
66	DNUM	Disconnect Line Number	<0001>
67	DISC NBR	Disconnect Telephone Number	<727SW07915>

Activity	Description		Service Type
Local Number	Port out telephone number		Number Portability
Portability			
No.	Field	Data Description	Wise/EDI Input
<i>Local Service Request Form (LSR)</i>			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<9722732425>
17	D/TSENT	Date and Time Sent	<200606090800>
19	DDD	Desired Date Due	<20060609>
30	REQTYP	Request Type	CB
33	ACT	Activity	V
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider Identification	<Z001>
52	AGAUTH	Agency Authorization Status	Y
61	LSO	Local Serving Office	<972273>
62	TOS	Type of Service	11F1
77	NPDI	Number Portability Direction Indicator	<C> (See Footnote 1)
105	INIT	Initiator Name	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
7	LOCNUM	Location Number	<01>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address Number	<210>
15	SASD	Service Address Street Directional Prefix	<S>
16	SASN	Service Address Street Name	<MAIN>
17	SATH	Service Address Street Type	<ST>
26	CITY	City	<Anytown>
27	STATE	State/Province	<TX>
28	ZIP	Zip/Postal Code	<75060>
39	ELT	End User Listing Treatment	C
45	EATN	Existing Account Telephone Number	<9722732425>
Number Portability Form (NP)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
10	LNA	Line Activity	V
13	LRN	Location Routing Number	<9722732425>
14	TDT	Ten Digit Trigger	Y
17	PORTED NBR	Ported Telephone Number	<9722732425>
20	NPT	Number Portability Type	D

Directory Listing Form (DL) 1			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
9	LACT	Listing Activity Indicator	D
10	ALI	Alpha/Numeric Listing Identifier Code	<100>
11	RTY	Record Type	<LML>
12	LTY	Listing Type	<3>
14	STYC	Style Code	<SL>
15	TOA	Type of Account	
16	DOI	Degree of Indent	<0>
18	LOCNUM	Location Number	<001>
19	DLNUM	Directory Listing Number	<0001>
20	MTN	Main Telephone Number	<9722732425>
38	LTN	Listing Telephone Number	<9722732425>
43	LEX	Local Exchange	<972273>
46	LNLN	Listed Name Last	<Best>
47	LNFN	Listed Name First	<Food Shop>
Footnotes:			
			1. Identifies the direction of the number port conversion activity on this request. 'B' = Wireless to Wireline 'C' = Wireline to Wireless 'D' = Wireline to Wireline See Business Rules for the appropriate entry.

Activity	Description	Service Type	
Migration	Migrate CLEC to CLEC	Loop	
	Take Loop		
No.	Field	Data Description	Business Rules Entry
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ2>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<817TX00019>
17	D/TSENT	Date and Time Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
24	DFDT	Desired Frame Due Time	<1200PM> (See Footnote 1)
29	CHC	Coordinated Hot Cut	<Y>
30	REQTYP	Request Type	AB
32	SLI	Sub-Loop Indicator	S
33	ACT	Activity	V
40	RVER	Release Version	<9>
43	CC	Company Code	<Z002>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	SPTWTXXADS0
61	LSO	Local Serving Office	817523
62	TOS	Type of Service	11F1 (See Footnote 2)
64	NC	Network Channel Code	LX--
66	NCI	Network Channel Interface Code	02QC2.OOF
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
115	IMPCON	Implementation Contact	<Mary Williams> (See Footnote 3)
116	TEL NO	Telephone Number	<8134383000> (See Footnote 3)

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shops>
13	SANO	Service Address House Number	<113>
15	SASD	Service Address Street Directional Prefix	W
16	SASN	Service Address Street Name	<SECOND>
17	SATH	Service Address Street Type	<ST>
26	CITY	City	<SPRINGTOWN>
27	STATE	State/Province	<TX>
28	ZIP	Zip/Postal Code	<76082>
39	ELT	End User Listing Treatment	A
45	EATN	Existing Account Telephone Number	817TX00019
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	V
34	SHELF	Shelf	AB
35	SLOT	Slot	99
Footnotes:			
			1. Time in the DFDT field should always be in Military Time (ie 0800 is 8:00AM, 1300 is 1:00 PM.) Time slots are allotted in 15-minute increments and are scheduled on a first come first serve basis. Morning hours with less than 4 characters should contain a leading zero (ie 0815)
			2. Refer to Business Rules for TOS guidelines and requirements.
			3. Required if DFDT is populated.

Activity	Description		Service Type
New Service	Establish New Loop Sharing Service		Loop
No.	Field Name	Description	Wise Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<N>
17	D/TSENT	Date and Time Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
30	REQTYP	Request Type	AB
32	SLI	Sub-Loop Indicator	S
33	ACT	Activity	N
43	CC	Company Code	<Z001>
40	RVER	Release Version	<9>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	VLEC CLLI
57	SACTL	Secondary Access Customer Terminal	DLEC CLLI
62	TOS	Type of Service	2FMN (See Footnote 1)
64	NC	Network Channel Code	URS-
66	NCI	Network Channel Interface Code	04QSM.L05
105	INIT	Initiator Identification	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279144>
115	IMPCON	Implementation Contact	<Mary Williams> (See Footnote 2)
116	TEL NO	Telephone Number	<8134383000> (See Footnote 2)

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<N>
9	NAME	End User Name	<Smith>
13	SANO	Service Address House Number	<330>
16	SASN	Service Address Street Name	<PHELPS>
17	SATH	Service Address Type	<DR>
26	CITY	City	<Anytown>
27	STATE	State/Province	<TX>
28	ZIP	Zip/Postal Code	<75038>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<N>
5	LQTY	Loop Quantity	2 (See Footnote 3)
Service Detail 1 (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	<N>
29	CTI	Connection Type Indicator	
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<99>
Service Detail 2 (SD)			
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00002>
9	LNA	Line Activity	<N>
29	CTI	Connection Type Indicator	<C>
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<99>
Footnotes			
			1. Refer to Business Rules for TOS guidelines and requirements.
			2. Required when LNA=N or T. Implementation Contact TEL NO required when IMPCON field is populated.
			3. Both data and voice services must be billed on the same account.

Activity	Description		Service Type
Partial Migration "as specified"	Migration from Line Sharing to Loop Sharing with Number Portability		Loop
No.	Field Name	Description	WISE Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZ1>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<9722732425>
17	D/TSENT	Date and Time Sent	<200606090800>
19	DDD	Desired Due Date	<20060609>
24	DFDT	Desired Frame Due Time	<2345> (See Footnote 1)
30	REQTYP	Request Type	BB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	V
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider Identification	<1234>
52	AGAUTH	Agency Authorization Status	<Y>
56	ACTL	Access Customer Terminal Location	VLEC CLLI
57	SACTL	Secondary Access Customer Terminal	DLEC CLLI
61	LSO	Local Serving Office	<972273>
62	TOS	Type of Service	2FMN (See Footnote 2)
64	NC	Network Channel Code	<URS->
66	NCI	Network Channel Interface Code	04QSM.L05
71	LSP AUTH	Local Service Provider Authorization	DLEC Identifier
77	NPDI	Number Portability Direction Indicator	D
87	ACNA	Access Customer Name Abbreviation	VLEC Identifier
105	INIT	Initiator Identification	<CTE>
106	TEL NO	Initiator Telephone Number	<8134833525>
115	IMPCON	Implementation Contact	<Mary Williams> (See Footnote 3)
116	TEL NO	Telephone Number	<8134383000> (See Footnote 3)

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Joe Smith>
27	STATE	State/Province	<TX>
28	ZIP	ZIP/Postal Code	<75060>
29	LCON	Local Contact	<Mary Smith>
30	TEL NO	Telephone Number	<9722734001>
39	ELT	End User Listing Treatment	<A>
45	EATN	Existing Account Telephone Number	<9722732425>
Loop Service with Number Portability Form (LSNP)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<9722732425>
5	LQTY	Loop Quantity	<2> (See Footnote 4)
Service Details (SD)			
8	LOCNUM	Location Number	<001>
9	LNUM	Line Number	<00001>
11	LNA	Line Activity	V
12	RL	Reuse Loop	Y
15	CKR	Customer Circuit Reference	<Identifies the CKT # assigned by the Customer>
22	OECCKT	Out ECCKT	<43.SWXX.508449..GTEC>
26a	CTI	Connection Type Indicator	
29	SHELF	Shelf	<ABC017>
30	SLOT	Slot	<99>
43	PORTED NBR	Ported Telephone Number	<9722732425>
46	NPT	Number Portability Type	D
Service Details (SD)			
8	LOCNUM	Location Number	<001>
9	LNUM	Line Number	<00002>
11	LNA	Line Activity	V
12	RL	Reuse Loop	Y
15	CKR	Customer Circuit Reference	<Identifies the CKT # assigned by the Customer>
22	OECCKT	Out ECCKT	<43.SWXX.508449..GTEC>
26a	CTI	Connection Type Indicator	<C>
29	SHELF	Shelf	<ABC017>
30	SLOT	Slot	<99>
43	PORTED NBR	Ported Telephone Number	<9722732425>
46	NPT	Number Portability Type	D

Footnotes

			1. Time in the DFDT field should always be in Military Time (ie 0800 is 8:00AM, 1300 is 1:00 PM.) Time slots are allotted in 15-minute increments and are scheduled on a first come first serve basis. Morning hours with less than 4 characters should contain a leading zero (ie 0815)
			2. Refer to Business Rules for TOS guidelines and requirements.
			3. Required if DFDT is populated.
			4. Both data and voice services must be billed on the same account.

Activity	Description	Service Type	
Post Migration	*Analog to Digital Loop Regrade	Loop	
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZZ>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<817TX00019>
17	D/TSENT	Date and Time Sent	<200606160800>
19	DDD	Desired Date Due	<20060621>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	C
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider Identification	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<SPTWTXXADS0>
61	LSO	Local Serving Office	<817523>
62	TOS	Type of Service	12F1 (See Footnote 1)
64	NC	Network Channel Code	LX-N (See Footnote 2)
66	NCI	Network Channel Interface Code	02QB9.00A (See Footnote 2)
105	INIT	Initiator Name	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address Number	<113>
16	SASN	Service Address Street Name	<SECOND>
17	SATH	Service Address Street Type	<ST>
26	CITY	City	<Anytown>
27	STATE	State/Province	<TX>
28	ZIP	Zip/Postal Code	<76082>
45	EATN	Existing Account Telephone Number	<817TX00019>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	C
17	ECCKT	Exchange Company Circuit ID	<2V.TXNU.000030. .GTEC>
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1001>

Footnotes			
			1. TOS 2nd and 3rd character = "2F" on existing analog to digital re-grades.
			2. See Local Business Rules.

Activity	Description	Service Type	
Post Migration	Digital to Analog Loop Regrade	Loop	
No.	Field	Data Description	Wise/EDI Input
Local Service Request Form (LSR)			
1	CCNA	Customer Carrier Name Abbreviation	<ZZZ>
2	PON	Purchase Order Number	<Your PON>
3	VER	Version	<01>
8	ATN	Account Telephone Number	<817TX00019>
17	D/TSENT	Date and Time Sent	<200606160800>
19	DDD	Desired Date Due	<20060621>
30	REQTYP	Request Type	AB
32	SLI	Sub Loop Indicator	S
33	ACT	Activity	C
40	RVER	Release Version	<9>
43	CC	Company Code	<Z001>
45	NNSP	New Network Service Provider Identification	<Z001>
52	AGAUTH	Agency Authorization Status	Y
56	ACTL	Access Customer Terminal Location	<SPTWTXXADS0>
61	LSO	Local Serving Office	<817523>
62	TOS	Type of Service	11F1 (See Footnote 1)
64	NC	Network Channel Code	LX-- (See Footnote 2)
66	NCI	Network Channel Interface Code	02QC2.OOF (See Footnote 2)
105	INIT	Initiator Name	<Joe Smith>
106	TEL NO	Initiator Telephone Number	<8134833525>
108	FAX NO	Facsimile Number	<8132279044>

End User Form (EU)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
9	NAME	End User Name	<Best Food Shop>
13	SANO	Service Address Number	<113>
16	SASN	Service Address Street Name	<SECOND>
17	SATH	Service Address Street Type	<ST>
26	CITY	City	<Anytown>
27	STATE	State/Province	<TX>
28	ZIP	Zip/Postal Code	<76082>
45	EATN	Existing Account Telephone Number	<817TX00019>
Loop Service Form (LS)			
1	PON	Purchase Order Number	<Your PON>
2	VER	Version	<01>
4	ATN	Account Telephone Number	<817TX00019>
7	LOCNUM	Location Number	<001>
8	LNUM	Line Number	<00001>
9	LNA	Line Activity	C
17	ECCKT	Exchange Company Circuit ID	<2V.TXNU.000030. .GTEC>
34	SHELF	Shelf	<ABC017>
35	SLOT	Slot	<1001>

Footnotes			
			1. TOS 2nd and 3rd character = "1F" on existing digital to analog re-grades.
			2. See Local Business Rules.