



| MODEL | Thunder 1501D | Thunder 801D | Thunder 421D | Thunder 311D | Thunder 251D | Thunder 895 | Thunder 1004 | Thunder 684 | Thunder 564 | Thunder 404 | Thunder 942 | Thunder 502 | Thunder 342 | Thunder 282 | Thunder 202 |
|-----------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|-------------------------------|
| 2 Ω Load | 1000 w x 1 | 500 w x 1 | 300 w x 1 | 200 w x 1 | 160 w x 1 | 320 w x 1 70 w x 4 | 180 w x 4 | 120 w x 4 | 90 w x 4 | 70 w x 4 | 350 w x 2 | 180 w x 2 | 120 w x 2 | 90 w x 2 | 70 w x 2 |
| 4 Ω Load | 500 w x 1 | 250 w x 1 | 150 w x 1 | 100 w x 1 | 80 w x 1 | 160 w x 1 35 w x 4 | 90 w x 4 | 60 w x 4 | 45 w x 4 | 35 w x 4 | 175 w x 2 | 90 w x 2 | 60 w x 2 | 45 w x 2 | 35 w x 2 |
| Bridged 4 Ω Load | | | | | | 140 w x 2 | 360 w x 2 | 240 w x 2 | 180 w x 2 | 140 w x 2 | 700 w | 360 w | 240 w | 180 w | 140 w |
| 2 Ω Load | 1500 w x 1 | 800 w x 1 | 420 w x 1 | 310 w x 1 | 250 w x 1 | 490 w x 1 100 w x 4 | 250 w x 4 | 170 w x 4 | 140 w x 4 | 100 w x 4 | 470 w x 2 | 250 w x 2 | 170 w x 2 | 140 w x 2 | 100 w x 2 |
| 4 Ω Load | 750 w x 1 | 400 w x 1 | 210 w x 1 | 155 w x 1 | 125 w x 1 | 245 w x 1 50 w x 4 | 125 w x 4 | 85 w x 4 | 70 w x 4 | 50 w x 4 | 235 w x 2 | 125 w x 2 | 85 w x 2 | 70 w x 2 | 50 w x 2 |
| Bridged 4 Ω Load | | | | | | 200 w x 2 | 500 w x 2 | 340 w x 2 | 280 w x 2 | 200 w x 2 | 940 w | 500 w | 340 w | 280 w | 200 w |
| Hi Level w/ Smart Engage | | X | X | X | X | | | | | X | | | X | X | X |
| Low Level | X | X | X | X | X | X | X | X | X | X | X | X | X | X | X |
| Input Select | | | | | | | X | X | X | X | | | | | |
| Hi / Low @ 85Hz | | | | | | | | | | | Rear Defeatable | | | Defeatable | Defeatable |
| Hi Pass @ 85Hz | | | | | | Front/Rear Defeatable | | | | | Front Defeatable | | | | |
| Low Pass @ 85Hz | | | | X | X | Sub Channel | | | | | | | | | |
| Hi / low @ | | | | | | | Front/Rear | Front/Rear | Front/Rear | | | | | | |
| Hi / low @ 40Hz-200Hz | | | | | | | Front/Rear | Front/Rear | Front/Rear | | Defeatable | Defeatable | Defeatable | | |
| Low Pass @ 40Hz-200Hz | X | X | X | | | | | | | | | | | | |
| Low Pass Only | X | X | X | | | | | | | | | | | | |
| Full Range Only | | | | X | X | | X | X | X | X | | | | X | X |
| Variable Hi, Low or Full Range | | | | | | | | | | | X | X | X | | |
| Compression Circuitry | X | X | | | | | | | | | X | X | | | |
| Thunder EQ | X | X | X | X | X | Sub | X | X | X | | X | X | X | | |
| EBC Port | X | X | X | | | Sub | | | | | X | X | | | |
| Dimensions With ISO Feet | 17.8" x 9.75" x 2.1" | 11.5" x 9.75" x 2.1" | 9.4" x 9.75" x 2.1" | 8" x 9.75" x 2.1" | 8" x 9.75" x 2.1" | 15.6" x 9.75" x 2.1" | 17.8" x 9.75" x 2.1" | 15.6" x 9.75" x 2.1" | 13.9" x 9.75" x 2.1" | 11.5" x 9.75" x 2.1" | 17.8" x 9.75" x 2.1" | 12.6" x 9.75" x 2.1" | 10.7" x 9.75" x 2.1" | 9.4" x 9.75" x 2.1" | 8" x 9.75" x 2.1" |
| | 45.3cm x 24.8cm x 5.3cm | 29.3cm x 24.8cm x 5.3cm | 23.9cm x 24.8cm x 5.3cm | 20.4cm x 24.8cm x 5.3cm | 20.4cm x 24.8cm x 5.3cm | 39.7cm x 24.8cm x 5.3cm | 45.3cm x 24.8cm x 5.3cm | 39.7cm x 24.8cm x 5.3cm | 35.4cm x 24.8cm x 5.3cm | 29.3cm x 24.8cm x 5.3cm | 45.3cm x 24.8cm x 5.3cm | 32.1cm x 24.8cm x 5.3cm | 27.2cm x 24.8cm x 5.3cm | 23.9cm x 24.8cm x 5.3cm | 20.4cm x 24.8cm x 5.3cm |